These instructions will assist in retrofitting retention ramp latch guards on a Tommy Gate Bi-Fold Railgate.

## Preparing for the Retrofit

- 1. Unfold and Position the platform at a comfortable working height.
- **2. Disconnect** all battery cables from the vehicle battery.

## Removing the Latch Assembly

- **3.** Loosen the Latch Bolt inside the Retention Ramp, but do not remove it at this time (Figures 1 and 2).
- **4. Loosen** the Latch Knob and **Remove** it from the Latch Block (Figures 1 and 2).

CAUTION: Latch Spring is under compression.

**5. Remove** the Latch Bolt, freeing the Latch Spring and Latch Block (Figures 1 and 2).

# Welding the Lid Guards

WARNING: Follow proper safety guidelines when welding near zinc plating.

- **6. Grind** away the zinc plating or paint where the Latch Guards will be welded.
- **7. Insert** the Locating Tool where the Latch Knob was removed (Figure 3).
- 8. Tack each Latch Guard using the Locating Tool as a guide (Figures 3 and 4).
- 9. Weld the Latch Guards in place (Figure 4).

## Painting the Retention Ramp End

- **10. Remove** any dirt, oil, grease, salt, or other contamination by washing with a mild detergent solution.
- 11. Rinse thoroughly with fresh water and allow to dry.
- 12. Lightly Scuff Sand the Tommy Gate topcoat.
- **13. Sand** and **Spot Prime** any area of the Tommy Gate paint that shows signs of damage.
- 14. Apply desired finish coat per paint manufacturer's recommendations.

# Reinstalling the Latch Assembly


- **15. Apply** blue thread locker to the threads on the Latch Knob.
- **16. Insert** the Latch Knob through the hole in the Retention Ramp End threading it into the Latch Block (Figure 2).
- 17. **Tighten** the Latch Knob so that no threads are showing.

CAUTION: Latch Spring is under compression.

- **18. Position** the Latch Spring as shown in Figure 2.
- **19. Insert** the bolt through the hole in the Retention Ramp End and **Thread** it into the Latch Block.
- **20. Tighten** the bolt with an open-end wrench while holding the Latch Block to lock the assembly into place.

### Finishing the Retrofit

- 21. Reconnect battery cables.
- **22. Return** the liftgate to the stowed position.






Figure 2: Remove/install latch assembly.




Figure 3: Locate latch guards.




Figure 5: Completed install.

Figure 4: Weld.

 $\bigcirc$ 

Latch

Guard

3/16"